

ecoled

DIY Cabinet Hinge Light

12v Cabinet Hinge Light

| Product Codes | RCH-CUB-DH2 |
|----------------------------|----------------------|
| | RCH-CUB-DH30 |
| | |
| Power (watts) | RCH-CUB-DH2 = 0.2w |
| | RCH-CUB-DH30 = 0.2w |
| | 10. 50 |
| Operating voltage | 12v DC |
| Lamp cap | Rechargeable |
| Expected Life (hours) | 30000 |
| Light output (lumens) | RCH-CUB-DH2 = 16 lm |
| | RCH-CUB-DH30 = 16 lm |
| | |
| Colour temperature | 6000k Cool White |
| Colour rendering index | >70 |
| Beam angle (degrees) | 120° |
| Dimming range | Non-dimmable |
| | |
| Dimensions (I x b x h) wt. | 68 x 42 x 25mm (20g) |
| | 68 x 42 x 25mm (20g) |











Place mounting plate over hinge screw hole

No electrician required Be careful of loostening hinges to

unsupported doors without assistance Fasten and use. No wiring required



Position and press light firmly onto mounting plate



Ajust positioning to activate light without limiting door movement



This nover little TZV cuppoard light fasteris directly onto most common cuppoard door ninges and triggers once the door is opened. It comes with a free 12v battery but can easily be connected to a 12v DC power

The RCH-CUB-DH2 uses 3 SMD 2835 LED chips that are angled to the back of the cupboard to give an even light spread throughout their 120° beam angle, while avoiding glare in your eyes.

The RCH-CUB-DH2 is a 2 unit pack that is ideal for one to two cupboard shelves. The RCH-CUB-DH30 is a contractors economy pack of 20 units all with their own battery included.

The life expectancy of these lights are 30000 hours and are NRCS & RoHS compliant.

These make great replacements for other cupboard lights like strip and batten lights, at a fraction of the

They require NO wiring and are completely self contained but can be connected to a grouped 12 DC power supply very easily if preferred.

These lights can accomodate a replacable rechargeable battery.

Order now to avoid disappointment. Stock arriving Mid April.